

WARNING

PLEASE READ ALL INSTRUCTIONS BEFORE ATTEMPTING INSTALLATION

- To prevent personal injury or product damage only licensed electricians should install.
- To avoid electric shock or component damage disconnect power before attempting installation or servicing.
- This product must be installed in accordance with the national electric code (NEC) and all applicable federal, state and local electric codes and safety standards.
- Disconnect product and allow cooling prior to servicing.
- Any alteration or modification of this product is expressly forbidden as it may cause serious personal injury, death, property damage and/or product malfunction.
- To prevent product malfunction and/or electrical shock this product must be properly grounded.
- This product must be installed in accordance with the applicable installation code by a Person familiar with the construction and operation of the product and the hazards involved.
- To prevent wiring damage or abrasion, do not expose wiring to shape edges of housing or other sharp surfaces.
- This device is not intend for use with emergency exit.
- If the lamp or luminaire exhibits undesirable operation (buzzing, flickering, etc.), immediately turn off power, remove the lamp from luminaire, and contactthe manufacturer.
- Designed for use with 100-277V 50-60Hz.
- Operating Temperature: -30°~60°C (-20°~140°F)

Installation

**MAKE SURE THE TO TURN OFF THE POWER AT THE BREAKER OR FUSE BOX
IF CCT AND WATTAGE SELECT MODEL ADJUST TO DESIRE OUTPUT BEFORE INSTALLATION**

Step 1: Turn off the power before beginning installation.

Step 2: Bypass the ballast, capacitor, and ignitor, where applicable. (Figure 1)

Step 3: Connect the two common wires from power source directly to the corresponding leads on socket.
Note: The socket of the lampholder must be CONNECTED to the NEUTRAL wire (white or gray). (Figure 2)

Step 4: Screw the Universal Light™ lamp into the fixture. Ensure that the bulb is seated firmly.

Step 5: Turn on the circuit breaker and AC switch.

Step 6: Turn on the ON / OFF Switch to verify proper operation.

